

The SDL DALI 3 channel is a constant voltage LED dimmer. The SDL DALI dimmer allows stepless brightness control via a DALI signal. LED dimmer drivers can be installed to meet the light needs of commercial or home lighting to reduce energy costs and to extend LED life span.

### SPECIFICATION

<b>Part No.</b>	SDL/DALI/3
<b>Supply Voltage</b>	12/24Vdc
<b>Output</b>	3 Channel
<b>Output Current (per channel)</b>	6 Amp
<b>Output Wattage (per channel)</b>	72W/12Vdc, 144W/24Vdc
<b>Dimming Control DALI Definition</b>	IEC62386 / IEC60929
<b>Size (LxWxH)</b>	153mm x 67mm x 30mm
<b>Drive Capability (per channel)</b>	3528/60 14 Max*
<i>With suitable power supply</i>	5050/60 5 Max*
	* Additional lengths can be driven using the SDL-RP306



### DIMENSIONS

